

# AS-i 3.0 POWERLINK Gateway in Stainless Steel, 2 masters

Recognition of duplicate AS-i addresses

AS-i Earth Fault Detector integrated

AS-i Noise Detector integrated

Optional Control III, programmable in C



(Figure similar)



Figure	Type	Model	Fieldbus interface <sup>(1)</sup>	Number of AS-i networks, number of AS-i Master <sup>(2)</sup>	1 power supply, 1 gateway for 2 AS-i networks, inexpensive power supplies <sup>(3)</sup>	Diagnostic and configuration interface <sup>(4)</sup>	Recognition of duplicate AS-i addresses <sup>(5)</sup>	AS-i fault detector <sup>(6)</sup>	Prog. in C <sup>(7)</sup>	Article no.
	POWER-LINK AS-i	Gateway	POWERLINK	2 AS-i networks, 2 AS-i Masters	no, max. 8 A/ AS-i network, redundant supply	Ethernet diagnostic	yes	yes	optional	<b>BWU3537</b>
	POWER-LINK AS-i	Gateway	POWERLINK	2 AS-i networks, 2 AS-i Masters	ja, max. 4 A/ AS-i network	Ethernet diagnostic	yes	yes	optional	<b>BWU3593</b>

**(1) Fieldbus interface**

Communication interface between fieldbus and gateway: interfaces for standardized fieldbus systems in industrial automation.  
**POWERLINK AS-i Gateway:** interface for a POWERLINK fieldbus

**(2) Number of AS-i networks, number of AS-i Master**

**"Double Master":** 2 AS-i networks, 2 AS-i Masters.

**(3) 1 power supply, 1 gateway for 2 AS-i networks, inexpensive power supplies**

**"no, max. 8 A/AS-i network, redundant supply":** 1 power supply per AS-i network. Gateway is powered in normal operation from one of the two AS-i power supplies. Should one AS-i power supply fail, switching to the other AS-i power supply allows all the diagnostics functions to be maintained and the unaffected AS-i network continues to operate.

**(4) Diagnostic and configuration interface**

**"Ethernet diagnostic":** Access to AS-i master and safety monitor with Bihl+Wiedemann proprietary software by using the Ethernet diagnostics interface.

**The latest version of the device description file of the gateway is available in the "Downloads" section of the respective device.**

**(5) Recognition of duplicate AS-i addresses**

Detects whether the same address has been assigned to two AS-i slaves. Frequent error when using a hand held addressing device.

**(6) AS-i fault detector**

Checks the AS-i line for interference effects such as noise, external voltages, etc.

**(7) Programming in C**

Using a C-program offers the possibility to run mini-PLC functions with a gateway.

# AS-i 3.0 POWERLINK Gateway in Stainless Steel, 2 masters

Article no.	BWU3537	BWU3593
<b>Interface</b>		
POWERLINK interface	<ul style="list-style-type: none"> <li>• 2 x RJ-45 Ethernet acc. to IEEE 802.3</li> <li>• integrated 2-Port-Switch</li> <li>• POWERLINK acc. to IEC 61748-2 and IEC 61158</li> </ul>	
Baud rates	100 MBaud	
Card slot	Chip card (128 KB) for storage of configuration data	
<b>AS-i</b>		
AS-i specification	3.0	
Cycle time	150 $\mu$ s * (number of slaves + 2)	
Operating voltage	30 V <sub>DC</sub> (20 ... 31,6 V)	
AS-i Power24V capability <sup>(1)</sup>	no	yes
<b>Display</b>		
LCD	menu, AS-i indication of slave addresses, error messages in plain text	
LED power (green)	power ON	
LED POWERLINK (green)	POWERLINK communication active	
LED config error (red)	configuration error	
LED U AS-i (green)	AS-i voltage o.k.	
LED AS-i active (green)	AS-i normal operation active	
LED prg enable (green)	automatic address programming enabled	
LED prj mode (yellow)	master is in configuration mode	
<b>UL-specifications (UL508)</b>		
External protection	An isolated source with a secondary open circuit voltage of $\leq 30$ V <sub>DC</sub> has to be protected with a 3 A maximum over current. Over current protection is not required when a Class 2 source is employed.	
In general	UL mark does not provide UL certification for any functional safety rating or aspects of the above devices.	
<b>Environment</b>		
Applied standards	EN 61000-6-2 EN 61000-6-4 EN 60529	
Housing	Stainless Steel, for DIN rail mounting	
Operating temperature	0 °C ... +55 °C	
Storage temperature	-25 °C ... +85 °C	
Pollution degree	2	
Protection category	IP20	
Tolerable loading referring to humidity	according to EN 61131-2	
Maximum tolerable shock and vibration stress	according to EN 61131-2	
Voltage of insulation	$\geq 500$ V	
Dimensions (W / H / D in mm)	85 / 120 / 83	
Weight	520 g	

<sup>(1)</sup> **AS-i Power24V**

The device can be operated directly on a 24 V (PELV) power supply. The gateway has been optimized with integrated data coupling coils and adjustable self-resetting fuses for safe use of powerful 24 V power supplies.

Article no.	Operating current		
	Master power supply, ca. 200 mA out of AS-i circuit	Master power supply, max. 200 mA out of AS-i circuit 1 (ca. 70 mA ... 200 mA), max. 200 mA out of AS-i circuit 2 (ca. 70 mA ... 200 mA); in sum max. 270 mA	Version „1 gateway, 1 power supply for 2 AS-i networks“, approx. 250 mA (PELV voltage)
BWU3537	-	•	-
BWU3593	-	-	•

## AS-i 3.0 POWERLINK Gateway in Stainless Steel, 2 masters

	BWU3537	BWU3593
Redundant power supply out of AS-i: all fundamental functions of the device remain available even in case of power failure in one of the two AS-i networks	•	–
Current measurement of the AS-i circuits	–	•
Self-resetting adjustable fuses	–	•
AS-i earth fault monitor distinguishes between AS-i cable and sensor cable	–	•
In version 1 gateway, 1 power supply for 2 AS-i networks: only 1 Gateway + 1 AS-i power supply for 2 AS-i networks	–	•

### Accessories:

- Chip card, memory capacity 128 KB (art. no. BW2222)
- Software for diagnostics, service and approval measurements (art. no. BW2902)
- Control III, Programming in C (art. no. BW2582)
- Power supplies, e.g.: AS-i power supply, 4 A (art. no. BW1649), AS-i power supply, 8 A (art. no. BW1997)  
(further power supply units can be found at [www.bihl-wiedemann.de/en/products/accessories/power-supplies](http://www.bihl-wiedemann.de/en/products/accessories/power-supplies))